# KEYLESS360

THE PERFECT RETROFIT LOCK

#### **EXPERIENCE THE PERFECT LOCKS**







EQUINOX



































# KEYLESS360

#### ARCHITECTURAL SPECIFICATIONS



PART NUMBER:
KEYLESS360-SN
KEYLESS360-SN-ADA

STANDARD FINISH: SATIN NICKEL



PART NUMBER: **KEYLESS360-MB** 

KEYLESS360-MB KEYLESS360-MB-ADA

PREMIUM FINISH: MATTE BLACK MUNSELL N2/



PART NUMBER:

KEYLESS360-MW KEYLESS360-MW-ADA

PREMIUM FINISH: MATTE WHITE MUNSELL N9/

#### 10% color discrepancy and custom pricing options apply.

- 2-digit alphanumeric combination
- Compatible with wood, glass, plastic, phenolic and metal locker doors
- One Master Key has 3 functions: bypasses the code, resets the lock, and retrieves the code - all conveniently from the front.
- Lock features reprogrammable-cylinder. When Master Key is lost or stolen, new Master Key is issued. Simply insert new Master Key and cylinder is reprogrammed - patented solution
- · Anti-pick and tamper resistant
- Self-correcting, Breakaway Knob protects against forced entry patented solution
- IP69K Complete dust and water resistance


- Strong 100% metal for long-term and heavy-use no plastic components.
- Large, clear combination digits, double the size of any competitors (5mm tall), that don't fade
- Sufficient digit and dial spacing that prevents accidental lockouts
- Strongest latch (bolt) in the industry and cannot be forced unlocked
- Dead bolt or spring bolt latch type (standard offset: 31mm - additional available)
- Simple 2 screw installation
- · Surface mounted
- Accommodates doors 1-21mm thickness

- Easily retrofits from most locks on most locker doors. "The Ultimate Retrofit Lock"
- Ergonomic non-slip grip
- One step twist-&-pull operation
- Knob rotates 90 degrees (from 12 o'clock to 3 o'clock) on left and right hand locks
- · Latch is simply interchangeable to left or right
- Clear locked and unlocked status indicator is visible from a distance
- Disinfected by misting with a liquid that is 70%-80% alcohol without damaging the surface of the lock
- Immediate live response during business hours
   no run around. (sos@keyless.co or 972.331.2770)


## TOP VIEW 1-6MM DOOR THICKNESS

# (0.1181in) (0.1181in) (1.2204in) (1.2204in)


## TOP VIEW 6-21MM DOOR THICKNESS



#### **FRONT VIEW**




#### DOOR ROUTING



#### 2010 & 2012 ADA STANDARDS FOR ACCESSIBLE DESIGN REQUIREMENTS



- 5% of lockers and their operable parts, the locks, must meet ADA specifications.
- Locks shall be operable with one hand.
- Shall not require tight grasping, pinching, or twisting of the wrist to operate.
- Shall have a force required to activate of 5lbs (22.2N) maximum.
- $\bullet$  Locks shall be installed maximum 48.00"/1220mm from the floor surface.



Manufactured By:



# KEYLESS360

**INSTRUCTIONS** 

# **USER INSTRUCTIONS**

#### **TO LOCK**

- 1. Close the door.
- 2. Make sure knob is pointing up to ∆, then set any 2-digit code.
- 3. Turn knob to  $\triangle$ .
- 4. Scramble the dials.

#### **CLICK LINK:**

https://www.keyless.co/keyless360/instructions/user/

#### **TO UNLOCK**

- 1. Re-enter your code.
- 2. Turn the knob up to  $\triangle$ .
- 3. Open the door.
- 4. Keeping the knob facing ☐, scramble the dials for the next user.

SCAN QR CODE TO VIEW USER INSTRUCTION VIDEO:



### MANAGER INSTRUCTIONS

#### **MASTER KEY CODE BYPASS**

(immediate manager access without code obstruction)

- 1. Insert the Master Key pointing towards the  $\triangle$ .
- 2. Turn the knob to â and access the locker, then close the door while keeping the knob facing â.
- 3. Return the knob to the △ position, and remove the key.
- \*Locker will remain locked and code will remain the same.

#### **USER CODE RETRIEVAL & RESET**

(retrieve forgotten user code and reset code for new user)

- 1. Insert the Master Key pointing towards the  $\triangle$  and turn the knob to  $\triangle$ .
- 2. With each dial: spin until it stops.
  - After setting each dial, the last used code will display.

#### **CLICK LINK:**

https://www.keyless.co/keyless360/instructions/reset/

- 3. Turn the knob back to  $\triangle$  and remove the key.

SCAN QR CODE TO VIEW
CODE RETRIEVAL & RESET
INSTRUCTION VIDEO:



